

Sat-IF-Distribution-Multiswitch

Multiswitch 5 in 24 / 32 Receiver powered

BMS 51-24R

BMS 51-32R

- multiswitch with 4 Sat + terrestrial input to 24 / 32 outputs
- latest RF-chipset technology
- integrated amplifier for low insertion loss
- High isolation between polarisations
- high isolation between polarisations
- return loss < 10 dB (low bit errors)
- integrated preemphasis for cable loss compensation
- Receiver powered
- Made in Germany



Type	BMS 51-24R		BMS 51-32R	
Feature	for Quad and Quattro LNB's, terr. passive			
User outputs	24		32	
Inputs	1 x terr.	4 x Sat	1 x terr.	4 x Sat
Frequency range	5-862 MHz	950-2150 MHz	5-862 MHz	950-2150 MHz
Insertion loss (Terr. passive/active)	32 dB	4...1 dB	32 dB	4...1 dB
Isolation polarisations	-	30 dB	-	30 dB
Subscriber decoupling	25 dB	25 dB	25 dB	25 dB
Max. output level	passive	102 dB μ V *	passive	102 dB μ V *
Ver./hor. Input control	12-14,5 V / 16-19 V			
Low/high band control	0 / 22 kHz			
Current consumption / subscriber	65 mA			
Max. total remote feed current	300 mA			
Secondary voltage (option)	18 V			
Ambient temperature range	-20 bis +55°C			
Dimensions	245 x 134 x 58 mm			
Weight	500 g		500 g	

* Terr. EN50083-5, 60-dBKMA, SAT EN50083-3, 35-dB-IMA,

Änderungen vorbehalten! / Subjects to change without notification!